

Telephone Number Change Procedure

Panasonic Model KX-D4930

(Internal Printer, with Screen)

1. Turn Power On
2. Press the Function Key "F1" (in top row of "chiclet" keys), **Phone Directory**.
3. Locate the row in table that contain our information. There should be "*" in the TEL and PRM columns for that row.
4. Press the Function Key "F5", **Add/Edit Entry**. Follow the instructions below.
 - i. (Edit Index) := _____ (Enter the entry for row that has the old information found in step 3.)
 - ii. (Name) : _____ (There should be a name currently TMK or MLS.)
(Press the Down Arrow Key "↓")
 - ii. (Phone Number) : _____ (Change the phone number to dial the new courtesy number.)
(**Oahu:** 441-0001, **Maui:** 442-0001, **Hilo / Kona:** 934-9058 / 443-0001 and **Kauai:** 246-2800)
 - iii. Press the Function Key "F1", **Private Parameter**.
 - iv. You should see a message at the bottom of the screen "**Edit Parameter**".
 - v. Press the Function Key "F1", **Edit Parameter**.
 - vi. Press the Down Arrow Key "↓" until the row labeled **Parity** is highlighted.
 - vii. Press the Function Key "F5", **None**.
 - viii. Press the Down Arrow Key "↓" again until the row labeled "**Word Length**" is highlighted.
 - viii. Press the Function Key "F2", **8**
 - ix. Press the Down Arrow Key "↓" until the row labeled **Transmit Code on 'BACK SPACE'** is highlighted.
 - x. Press the Function Key "F2", **Del**.
 - xi. Press the Down Arrow Key "↓" until the row labeled **Detect XON/XOFF busy code** is highlighted.
 - xii. Press the Function Key "F2", **Yes**.
 - xiii. Press the **BREAK** Key.
 - ix. Press the Function Key "F2", **Auto Logon**.
 - x. You should see three columns, the left column says **STEP**, the middle column says **COMMAND**, and the right column says **CHARACTERS** at the top of the screen.

xi. Press the Function Key "F4", the word **Transmit** is printed under the Command column and press Return and a funny character that looks like cr will be printed under the Characters column.

xii. Press the Down Arrow Key "↓" and press the Function Key "F3", for **Trigger On** and type a close parenthesis ()

xii. Press the Down Arrow Key "↓" and press the Function Key "F4", for **Transmit** and type 2 and press Return for the cr funny character.

xiii. Press the Down Arrow Key "↓" and then press the Function Key "F8" twice and Press the Function Key "F5" for **Exit**.

After you complete steps xi-xvi, you will have a screen that looks something like the one on **FIGURE 1** below.

xxi. Press the **BREAK** Key 4 times.

Now, you may press the blue **ONLINE** button on the top right corner and then press the letter for the number you wish to dial.

```
AUTO LOGON          Index := A          Auto ans  FEB 9 '87  1:25 AM REPLACE
```

STEP	COMMAND	CHARACTERS
1	TRANSMIT	cr
2	TRIGGER ON	:
3	TRANSMIT	research3cr
4	TRIGGER ON	:
5	TRANSMIT	mlshawaii:cr
6	EXIT	

FIGURE 1